

# 3M™ Standard Interchange Protocol

**Describes 3M Standard Interchange Protocol Version 2.00**

Document Revision 2.12, Updated April 11, 2006

**78-8129-2375-9 Rev A.**

## Contents

Introduction.....	1
What’s New with the Standard Interchange Protocol?.....	2
Command Messages to the ACS.....	3
Response Messages from the ACS.....	8
Standard Protocol Rules and Regulations.....	14
Standalone Messages.....	14
Commands.....	14
Fields.....	14
Packet Format.....	14
Message Terminator.....	15
Nulls.....	15
Fixed-length fields.....	15
Variable-length fields.....	15
Establishing a Connection.....	15
Error Handling.....	15
Checksums and Sequence Numbers.....	15
SC System Error Handling.....	16
ACS System Error Handling.....	16
Protocol Version Compatibility.....	17
Protocol Extensions.....	17
Field identifiers for variable-length or optional fields.....	27
Message identifiers.....	28
<i>Revision History</i> .....	29

## *3M Standard Interchange Protocol*

© 1997, 1998, 2005 3M

Permission is hereby granted to utilize this protocol in hardware and software products but no permission is granted to create derivative works or otherwise modify the protocol.

**Important Notice:** The information in this Standard Interchange Protocol (SIP) is provided for use on an "AS IS" basis. 3M neither makes nor gives any representation or warranty, express or implied, concerning the information in this SIP including, but not limited to, the warranties of merchantability of fitness for a particular purpose. The user is solely responsible for determining the suitability of this information and bears all risk of its use.

# **Data Transfer Protocol Between Library Automation Devices and Automated Circulation Systems**

## **Introduction**

This protocol provides a standard interface between a library's Automated Circulation System (ACS) and library automation devices. The protocol was developed originally as an interface between the Automated Circulation System and 3M™ SelfCheck™ system. With the growth of automation in the library, there is an increased need for a standard protocol.

This standard protocol will be applicable to ACS system interfaces to automated devices and services where patron information and/or library material information is required.

This standard protocol benefits the library by enabling them to:

- Add new types of automated devices and services to the library with minimal change to the ACS system.
- Upgrade to new versions of automated devices with minimal or no change needed in the ACS system.
- Change from one ACS to another without the need to replace equipment or services that interface with the ACS.

This standard protocol description will be useful to:

- Vendors of library systems and devices who wish to develop a standard interface between the ACS and automated library devices.
- Library planning committees who are planning new types of automated devices and services for patrons or staff.

### Acronyms and Abbreviations

**ACS** = Automated Circulation System

**SC** = 3M SelfCheck system or any library automation device dealing with patrons or library materials

**NISO** = National (U.S.) International Standards Organization

If you have questions regarding the 3M Standard Interchange Protocol, you may call 3M Library Systems Software Support at 800-328-0067 option 1,1,1.

## **What's New with the Standard Interchange Protocol?**

This document describes Version 2.00 of the 3M Standard Interchange Protocol. Version 2.00 builds on top of Version 1.00 of the protocol, adding new messages, and new fields to already-existing messages. All new messages and fields are indicated by having "2.00" in front of them in the message definitions. Any messages and fields that are not prefixed by "2.00" existed in earlier versions of the protocol.

## Command Messages to the ACS

### Patron Status Request

This message is used by the SC to request patron information from the ACS. The ACS must respond to this command with a Patron Status Response message.

23<language><transaction date><institution id><patron identifier><terminal password><patron password>

<u>Field</u>	<u>ID</u>	<u>Format</u>
language		3-char, fixed-length required field
transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
institution id	AO	variable-length required field
patron identifier	AA	variable-length required field
terminal password	AC	variable-length required field
patron password	AD	variable-length required field

### Checkout

This message is used by the SC to request to check out an item, and also to cancel a Checkin request that did not successfully complete. The ACS must respond to this command with a Checkout Response message.

11<SC renewal policy><no block><transaction date><nb due date><institution id><patron identifier><item identifier><terminal password><patron password><item properties><fee acknowledged><cancel>

<u>Field</u>	<u>ID</u>	<u>Format</u>
SC renewal policy		1-char, fixed-length required field: Y or N.
no block		1-char, fixed-length required field: Y or N.
transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS. The date and time that the patron checked out the item at the SC unit.
nb due date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
institution id	AO	variable-length required field
patron identifier	AA	variable-length required field
item identifier	AB	variable-length required field
terminal password	AC	variable-length required field
<i>2.00 item properties</i>	<i>CH</i>	<i>variable-length optional field</i>
<i>2.00 patron password</i>	<i>AD</i>	<i>variable-length optional field</i>
<i>2.00 fee acknowledged</i>	<i>BO</i>	<i>1-char, optional field: Y or N</i>
<i>2.00 cancel</i>	<i>BI</i>	<i>1-char, optional field: Y or N</i>

### Checkin

This message is used by the SC to request to check in an item, and also to cancel a Checkout request that did not successfully complete. The ACS must respond to this command with a Checkin Response message.

09<no block><transaction date><return date><current location><institution id><item identifier><terminal password><item properties><cancel>

<u>Field</u>	<u>ID</u>	<u>Format</u>
no block		1-char, fixed-length required field: Y or N.
transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
return date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
current location	AP	variable-length required field
institution id	AO	variable-length required field
item identifier	AB	variable-length required field
terminal password	AC	variable-length required field
<i>2.00 item properties</i>	<i>CH</i>	<i>variable-length optional field</i>
<i>2.00 cancel</i>	<i>BI</i>	<i>1-char, optional field: Y or N</i>

## Block Patron

This message requests that the patron card be blocked by the ACS. This is, for example, sent when the patron is detected tampering with the SC or when a patron forgets to take their card. The ACS should invalidate the patron's card and respond with a Patron Status Response message. The ACS could also notify the library staff that the card has been blocked.

01<card retained><transaction date><institution id><blocked card msg><patron identifier><terminal password>

<u>Field</u>	<u>ID</u>	<u>Format</u>
card retained		1-char, fixed-length required field: Y or N.
transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
institution id	AO	variable-length required field
blocked card msg	AL	variable-length required field
patron identifier	AA	variable-length required field
terminal password	AC	variable-length required field

## SC Status

The SC status message sends SC status to the ACS. It requires an ACS Status Response message reply from the ACS. This message will be the first message sent by the SC to the ACS once a connection has been established (exception: the Login Message may be sent first to login to an ACS server program). The ACS will respond with a message that establishes some of the rules to be followed by the SC and establishes some parameters needed for further communication.

99<status code><max print width><protocol version>

<u>Field</u>	<u>ID</u>	<u>Format</u>
status code		1-char, fixed-length required field: 0 or 1 or 2
max print width		3-char, fixed-length required field
protocol version		4-char, fixed-length required field: x.xx

## Request ACS Resend

This message requests the ACS to re-transmit its last message. It is sent by the SC to the ACS when the checksum in a received message does not match the value calculated by the SC. The ACS should respond by re-transmitting its last message. This message should never include a "sequence number" field, even when error detection is enabled, (see "Checksums and Sequence Numbers" below) but would include a "checksum" field since checksums are in use.

97

## 2.00 Login

This message can be used to login to an ACS server program. The ACS should respond with the Login Response message. Whether to use this message or to use some other mechanism to login to the ACS is configurable on the SC. When this message is used, it will be the first message sent to the ACS.

93<UID algorithm><PWD algorithm><login user id><login password><location code>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
2.00	UID algorithm		1-char, fixed-length required field; the algorithm used to encrypt the user id.
2.00	PWD algorithm		1-char, fixed-length required field; the algorithm used to encrypt the password.
2.00	login user id	CN	variable-length required field
2.00	login password	CO	variable-length required field
2.00	location code	CP	variable-length optional field; the SC location.

**2.00 Patron Information**

This message is a superset of the Patron Status Request message. It should be used to request patron information. The ACS should respond with the Patron Information Response message.

63<language><transaction date><summary><institution id><patron identifier><terminal password><patron password><start item><end item>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
	language		3-char, fixed-length required field
	transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
2.00	summary		10-char, fixed-length required field
	institution id	AO	variable-length required field
	patron identifier	AA	variable-length required field
	terminal password	AC	variable-length optional field
	patron password	AD	variable-length optional field
2.00	start item	BP	variable-length optional field
2.00	end item	BQ	variable-length optional field

**2.00 End Patron Session**

This message will be sent when a patron has completed all of their transactions. The ACS may, upon receipt of this command, close any open files or deallocate data structures pertaining to that patron. The ACS should respond with an End Session Response message.

35<transaction date><institution id><patron identifier><terminal password><patron password>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
	transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
	institution id	AO	variable-length required field
	patron identifier	AA	variable-length required field.
	terminal password	AC	variable-length optional field
	patron password	AD	variable-length optional field

**2.00 Fee Paid**

This message can be used to notify the ACS that a fee has been collected from the patron. The ACS should record this information in their database and respond with a Fee Paid Response message.

37<transaction date><fee type><payment type><currency type><fee amount><institution id><patron identifier><terminal password><patron password><fee identifier><transaction id>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
	transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
2.00	fee type		2-char, fixed-length required field (01 thru 99). identifies a fee type to apply the payment to.
2.00	payment type		2-char, fixed-length required field (00 thru 99)
2.00	currency type		3-char, fixed-length required field
2.00	fee amount	BV	variable-length required field; the amount paid.
	institution id	AO	variable-length required field
	patron identifier	AA	variable-length required field.
	terminal password	AC	variable-length optional field
	patron password	AD	variable-length optional field
2.00	fee identifier	CG	variable-length optional field; identifies a specific fee to apply the payment to.
2.00	transaction id	BK	variable-length optional field; a transaction id assigned by the payment device.

**2.00 Item Information**

This message may be used to request item information. The ACS should respond with the Item Information Response message.

17<transaction date><institution id>< item identifier ><terminal password>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
	transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
	institution id	AO	variable-length required field
	item identifier	AB	variable-length required field.
	terminal password	AC	variable-length optional field

**2.00 Item Status Update**

This message can be used to send item information to the ACS, without having to do a Checkout or Checkin operation. The item properties could be stored on the ACS's database. The ACS should respond with an Item Status Update Response message.

19<transaction date><institution id><item identifier><terminal password><item properties>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
	transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
	institution id	AO	variable-length required field
	item identifier	AB	variable-length required field
	terminal password	AC	variable-length optional field
2.00	<i>item properties</i>	CH	<i>variable-length required field</i>

## 2.00 Patron Enable

This message can be used by the SC to re-enable canceled patrons. It should only be used for system testing and validation. The ACS should respond with a Patron Enable Response message.

25<transaction date><institution id><patron identifier><terminal password><patron password>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
	transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
	institution id	AO	variable-length required field
	patron identifier	AA	variable-length required field
	terminal password	AC	variable-length optional field
	patron password	AD	variable-length optional field

## 2.00 Hold

This message is used to create, modify, or delete a hold. The ACS should respond with a Hold Response message. Either or both of the "item identifier" and "title identifier" fields must be present for the message to be useful.

15<hold mode><transaction date><expiration date><pickup location><hold type><institution id><patron identifier><patron password><item identifier><title identifier><terminal password><fee acknowledged>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
2.00	<i>hold mode</i>		<i>1-char, fixed-length required field '+'/'-'/'*' Add, delete, change</i>
	transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
2.00	<i>expiration date</i>	BW	<i>18-char, fixed-length optional field: YYYYMMDDZZZZHHMMSS</i>
2.00	<i>pickup location</i>	BS	<i>variable-length, optional field</i>
2.00	<i>hold type</i>	BY	<i>1-char, optional field</i>
	institution id	AO	variable-length required field
	patron identifier	AA	variable-length required field
	patron password	AD	variable-length optional field
	item identifier	AB	variable-length optional field
	title identifier	AJ	variable-length optional field
	terminal password	AC	variable-length optional field
2.00	<i>fee acknowledged</i>	BO	<i>1-char, optional field: Y or N.</i>

## 2.00 Renew

This message is used to renew an item. The ACS should respond with a Renew Response message. Either or both of the "item identifier" and "title identifier" fields must be present for the message to be useful.

29<third party allowed><no block><transaction date><nb due date><institution id><patron identifier><patron password><item identifier><title identifier><terminal password><item properties><fee acknowledged>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
2.00	<i>third party allowed</i>		<i>1-char, fixed-length required field: Y or N.</i>
	no block		1-char, fixed-length required field: Y or N.
	transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
	nb due date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
	institution id	AO	variable-length required field
	patron identifier	AA	variable-length required field
	patron password	AD	variable-length optional field
	item identifier	AB	variable-length optional field
	title identifier	AJ	variable-length optional field



	terminal password	AC	variable-length optional field
2.00	<i>item properties</i>	CH	<i>variable-length optional field</i>
2.00	<i>fee acknowledged</i>	BO	<i>1-char, optional field: Y or N.</i>

## 2.00 **Renew All**

This message is used to renew all items that the patron has checked out. The ACS should respond with a Renew All Response message.

65<transaction date><institution id><patron identifier><patron password><terminal password><fee acknowledged>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
	transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
	institution id	AO	variable-length required field
	patron identifier	AA	variable-length required field
	patron password	AD	variable-length optional field
	terminal password	AC	variable-length optional field
2.00	<i>fee acknowledged</i>	BO	<i>1-char, optional field: Y or N.</i>

## Response Messages from the ACS

### Patron Status Response

The ACS must send this message in response to a Patron Status Request message as well as in response to a Block Patron message.

24<patron status><language><transaction date><institution id><patron identifier><personal name><valid patron><valid patron password><currency type><fee amount><screen message><print line>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
	patron status		14-char, fixed-length required field
	language		3-char, fixed-length required field
	transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
	institution id	AO	variable-length required field
	patron identifier	AA	variable-length required field
	personal name	AE	variable-length required field
2.00	<i>valid patron</i>	BL	1-char, optional field: Y or N
2.00	<i>valid patron password</i>	CQ	1-char, optional field: Y or N
2.00	<i>currency type</i>	BH	3-char, fixed-length optional field
2.00	<i>fee amount</i>	BV	variable-length optional field. <i>The amount of fees owed by this patron.</i>
	screen message	AF	variable-length optional field
	print line	AG	variable-length optional field

### Checkout Response

This message must be sent by the ACS in response to a Checkout message from the SC.

12<ok><renewal ok><magnetic media><desensitize><transaction date><institution id><patron identifier><item identifier><title identifier><due date><fee type><security inhibit><currency type><fee amount><media type><item properties><transaction id><screen message><print line>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
	ok		1-char, fixed-length required field: 0 or 1.
	renewal ok		1-char, fixed-length required field: Y or N.
	magnetic media		1-char, fixed-length required field: Y or N or U.
	desensitize		1-char, fixed-length required field: Y or N or U.
	transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
	institution id	AO	variable-length required field
	patron identifier	AA	variable-length required field
	item identifier	AB	variable-length required field
	title identifier	AJ	variable-length required field
	due date	AH	variable-length required field
2.00	<i>fee type</i>	BT	2-char, fixed-length optional field (01 thru 99). <i>The type of fee associated with checking out this item.</i>
2.00	<i>security inhibit</i>	CI	1-char, fixed-length optional field: Y or N.
2.00	<i>currency type</i>	BH	3-char fixed-length optional field
2.00	<i>fee amount</i>	BV	variable-length optional field. <i>The amount of the fee associated with checking out this item.</i>
2.00	<i>media type</i>	CK	3-char, fixed-length optional field
2.00	<i>item properties</i>	CH	variable-length optional field
2.00	<i>transaction id</i>	BK	variable-length optional field. <i>May be assigned by the ACS when checking out the item involves a fee.</i>
	screen message	AF	variable-length optional field
	print line	AG	variable-length optional field

The OK, Renewal OK, Desensitize, Magnetic Media, and Fee Amount fields should be set according to the following rules:

OK	should be set to 1 if the ACS checked out the item to the patron. should be set to 0 if the ACS did not check out the item to the patron.
Renewal OK	should be set to Y if the patron requesting to check out the item already has the item checked out should be set to N if the item is not already checked out to the requesting patron. Desensitize should be set to Y if the SC should desensitize the article. should be set to N if the SC should not desensitize the article (for example, a closed reserve book, or the checkout was refused).
Fee Amount	should be set to the value of the fee associated with checking out the item should be set to 0 if there is no fee associated with checking out the item.

### Checkin Response

This message must be sent by the ACS in response to a SC Checkin message.

10<ok><resensitize><magnetic media><alert><transaction date><institution id><item identifier><permanent location><title identifier><sort bin><patron identifier><media type><item properties><screen message><print line>

Field	ID	Format
ok		1-char, fixed-length required field: 0 or 1.
resensitize		1-char, fixed-length required field: Y or N.
magnetic media		1-char, fixed-length required field: Y or N or U.
alert		1-char, fixed-length required field: Y or N.
transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
institution id	AO	variable-length required field
item identifier	AB	variable-length required field
permanent location	AQ	variable-length required field
title identifier	AJ	variable-length optional field
<b>2.00</b> <i>sort bin</i>	CL	<i>variable-length optional field</i>
<b>2.00</b> <i>patron identifier</i>	AA	<i>variable-length optional field. ID of the patron who had the item checked out.</i>
<b>2.00</b> <i>media type</i>	CK	<i>3-char, fixed-length optional field</i>
<b>2.00</b> <i>item properties</i>	CH	<i>variable-length optional field</i>
screen message	AF	variable-length optional field
print line	AG	variable-length optional field

The OK, and Resensitize fields should be set according to the following rules:

OK	should be set to 1 if the ACS checked in the item. should be set to 0 if the ACS did not check in the item.
Resensitize	should be set to Y if the SC should resensitize the article. should be set to N if the SC should not resensitize the article (for example, a closed reserve book, or the checkin was refused).

### ACS Status

The ACS must send this message in response to a SC Status message. This message will be the first message sent by the ACS to the SC, since it establishes some of the rules to be followed by the SC and establishes some parameters needed for further communication (exception: the Login Response Message may be sent first to complete login of the SC).

98<on-line status><checkin ok><checkout ok><ACS renewal policy><status update ok><off-line ok><timeout period><retries allowed><date / time sync><protocol version><institution id><library name><supported messages><terminal location><screen message><print line>

Field	ID	Format
on-line status		1-char, fixed-length required field: Y or N.
checkin ok		1-char, fixed-length required field: Y or N.
checkout ok		1-char, fixed-length required field: Y or N.
ACS renewal policy		1-char, fixed-length required field: Y or N.
status update ok		1-char, fixed-length required field: Y or N.
off-line ok		1-char, fixed-length required field: Y or N.
timeout period		3-char, fixed-length required field
retries allowed		3-char, fixed-length required field
date / time sync		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
protocol version		4-char, fixed-length required field: x.xx
institution id	AO	variable-length required field

	library name	AM	variable-length optional field
2.00	supported messages	BX	variable-length required field
	terminal location	AN	variable-length optional field
	screen message	AF	variable-length optional field
	print line	AG	variable-length optional field

### Request SC Resend

This message requests the SC to re-transmit its last message. It is sent by the ACS to the SC when the checksum in a received message does not match the value calculated by the ACS. The SC should respond by re-transmitting its last message. This message should never include a “sequence number” field, even when error detection is enabled, (see “Checksums and Sequence Numbers” below) but would include a “checksum” field since checksums are in use.

96

### 2.00 Login Response

The ACS should send this message in response to the Login message. When this message is used, it will be the first message sent to the SC.

94&lt;ok&gt;

<u>Field</u>	<u>ID</u>	<u>Format</u>
ok		1-char, fixed-length required field: 0 or 1.

### 2.00 Patron Information Response

The ACS must send this message in response to the Patron Information message.

64<patron status><language><transaction date><hold items count><overdue items count><charged items count><fine items count><recall items count><unavailable holds count><institution id><patron identifier><personal name><hold items limit><overdue items limit><charged items limit><valid patron><valid patron password><currency type><fee amount><fee limit><items><home address><e-mail address><home phone number><screen message><print line>

<u>Field</u>	<u>ID</u>	<u>Format</u>
patron status		14-char, fixed-length required field
language		3-char, fixed-length required field
transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
2.00 hold items count		4-char, fixed-length required field
2.00 overdue items count		4-char, fixed-length required field
2.00 charged items count		4-char, fixed-length required field
2.00 fine items count		4-char, fixed-length required field
2.00 recall items count		4-char, fixed-length required field
2.00 unavailable holds count		4-char, fixed-length required field
institution id	AO	variable-length required field
patron identifier	AA	variable-length required field
personal name	AE	variable-length required field
2.00 hold items limit	BZ	4-char, fixed-length optional field
2.00 overdue items limit	CA	4-char, fixed-length optional field
2.00 charged items limit	CB	4-char, fixed-length optional field
2.00 valid patron	BL	1-char, optional field: Y or N
2.00 valid patron password	CQ	1-char, optional field: Y or N
2.00 currency type	BH	3-char fixed-length optional field
2.00 fee amount	BV	variable-length optional field. The amount of fees owed by this patron.
2.00 fee limit	CC	variable-length optional field. The fee limit amount.

item: zero or more instances of one of the following, based on “summary” field of the Patron Information message:

2.00 hold items	AS	variable-length optional field (this field should be sent for each hold item).
2.00 overdue items	AT	variable-length optional field (this field should be sent for each overdue item).
2.00 charged items	AU	variable-length optional field (this field should be sent for each charged item).
2.00 fine items	AV	variable-length optional field (this field should be sent for each fine item).
2.00 recall items	BU	variable-length optional field (this field should be sent for each recall item).
2.00 unavailable hold items	CD	variable-length optional field (this field should be sent for each unavailable hold item).
2.00 home address	BD	variable-length optional field

2.00	e-mail address	BE	variable-length optional field
2.00	home phone number	BF	variable-length optional field
	screen message	AF	variable-length optional field
	print line	AG	variable-length optional field

## 2.00 End Session Response

The ACS must send this message in response to the End Patron Session message.

36<end session>< transaction date >< institution id >< patron identifier ><screen message><print line>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
2.00	end session		1-char, fixed-length required field: Y or N.
	transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
	institution id	AO	variable-length required field
	patron identifier	AA	variable-length required field.
	screen message	AF	variable-length optional field
	print line	AG	variable-length optional field

## 2.00 Fee Paid Response

The ACS must send this message in response to the Fee Paid message.

38<payment accepted><transaction date><institution id><patron identifier><transaction id><screen message><print line>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
2.00	payment accepted		1-char, fixed-length required field: Y or N.
	transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
	institution id	AO	variable-length required field
	patron identifier	AA	variable-length required field
2.00	transaction id	BK	variable-length optional field. May be assigned by the ACS to acknowledge that the payment was received.
	screen message	AF	variable-length optional field
	print line	AG	variable-length optional field

## 2.00 Item Information Response

The ACS must send this message in response to the Item Information message.

18<circulation status><hold queue length><security marker><fee type><transaction date><due date><recall date><hold pickup date><item identifier><title identifier><owner><currency type><fee amount><media type><permanent location><current location><item properties><screen message><print line>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
2.00	circulation status		2-char, fixed-length required field (00 thru 99)
2.00	security marker		2-char, fixed-length required field (00 thru 99)
2.00	fee type		2-char, fixed-length required field (01 thru 99). The type of fee associated with checking out this item.
	transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
2.00	hold queue length	CF	variable-length optional field
	due date	AH	variable-length optional field.
2.00	recall date	CJ	18-char, fixed-length optional field: YYYYMMDDZZZZHHMMSS
2.00	hold pickup date	CM	18-char, fixed-length optional field: YYYYMMDDZZZZHHMMSS
	item identifier	AB	variable-length required field
	title identifier	AJ	variable-length required field
2.00	owner	BG	variable-length optional field
2.00	currency type	BH	3 char, fixed-length optional field
2.00	fee amount	BV	variable-length optional field. The amount of the fee associated with this item.
2.00	media type	CK	3-char, fixed-length optional field
2.00	permanent location	AQ	variable-length optional field
2.00	current location	AP	variable-length optional field
2.00	item properties	CH	variable-length optional field
	screen message	AF	variable-length optional field
	print line	AG	variable-length optional field

## 2.00 Item Status Update Response

The ACS must send this message in response to the Item Status Update message.

20<item properties ok><transaction date><item identifier><title identifier><item properties><screen message><print line>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
2.00	item properties ok		1-char, fixed-length required field: 0 or 1.
	transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
	item identifier	AB	variable-length required field
	title identifier	AJ	variable-length optional field
2.00	item properties	CH	variable-length optional field
	screen message	AF	variable-length optional field
	print line	AG	variable-length optional field

## 2.00 Patron Enable Response

The ACS should send this message in response to the Patron Enable message from the SC.

26<patron status><language><transaction date><institution id><patron identifier><personal name><valid patron><valid patron password><screen message><print line>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
	patron status		14-char, fixed-length required field
	language		3-char, fixed-length required field
	transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
	institution id	AO	variable-length required field
	patron identifier	AA	variable-length required field
	personal name	AE	variable-length required field
2.00	valid patron	BL	1-char, optional field: Y or N.
2.00	valid patron password	CQ	1-char, optional field: Y or N
	screen message	AF	variable-length optional field
	print line	AG	variable-length optional field

## 2.00 Hold Response

The ACS should send this message in response to the Hold message from the SC.

16<ok><available><transaction date><expiration date><queue position><pickup location><institution id><patron identifier><item identifier><title identifier><screen message><print line>

	<u>Field</u>	<u>ID</u>	<u>Format</u>
	ok		1-char, fixed-length required field: 0 or 1.
2.00	available		1-char, fixed-length required field: Y or N.
	transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
2.00	expiration date	BW	18-char, fixed-length optional field: YYYYMMDDZZZZHHMMSS
2.00	queue position	BR	variable-length optional field
2.00	pickup location	BS	variable-length optional field
	institution id	AO	variable-length required field
	patron identifier	AA	variable-length required field
	item identifier	AB	variable-length optional field
	title identifier	AJ	variable-length optional field
	screen message	AF	variable-length optional field
	print line	AG	variable-length optional field

**2.00 Renew Response**

This message must be sent by the ACS in response to a Renew message by the SC.

30<ok><renewal ok><magnetic media><desensitize><transaction date><institution id><patron identifier><item identifier><title identifier><due date><fee type><security inhibit><currency type><fee amount><media type><item properties><transaction id><screen message><print line>

<u>Field</u>	<u>ID</u>	<u>Format</u>
ok		1-char, fixed-length required field: 0 or 1.
renewal ok		1-char, fixed-length required field: Y or N.
magnetic media		1-char, fixed-length required field: Y or N or U.
desensitize		1-char, fixed-length required field: Y or N or U.
transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
institution id	AO	variable-length required field
patron identifier	AA	variable-length required field
item identifier	AB	variable-length required field
title identifier	AJ	variable-length required field
due date	AH	variable-length required field
<b>2.00</b> fee type	<b>BT</b>	<b>2-char, fixed-length optional field (01 thru 99). The type of fee associated with renewing this item.</b>
<b>2.00</b> security inhibit	<b>CI</b>	<b>1-char, fixed-length optional field: Y or N.</b>
<b>2.00</b> currency type	<b>BH</b>	<b>3-char fixed-length optional field</b>
<b>2.00</b> fee amount	<b>BV</b>	<b>variable-length optional field. The amount of the fee associated with this item.</b>
<b>2.00</b> media type	<b>CK</b>	<b>3-char, fixed-length optional field</b>
<b>2.00</b> item properties	<b>CH</b>	<b>variable-length optional field</b>
<b>2.00</b> transaction id	<b>BK</b>	<b>variable-length optional field. May be assigned by the ACS when renewing the item involves a fee.</b>
screen message	AF	variable-length optional field
print line	AG	variable-length optional field

See the description of the Checkout Response message for how the ok, renewal ok, desensitize, and fee amount fields will be interpreted.

**2.00 Renew All Response**

The ACS should send this message in response to a Renew All message from the SC.

66<ok ><renewed count><unrenewed count><transaction date><institution id><renewed items><unrenewed items><screen message><print line>

<u>Field</u>	<u>ID</u>	<u>Format</u>
ok		1-char, fixed-length required field: 0 or 1
<b>2.00</b> renewed count		<b>4-char fixed-length required field</b>
<b>2.00</b> unrenewed count		<b>4-char fixed-length required field</b>
transaction date		18-char, fixed-length required field: YYYYMMDDZZZZHHMMSS
institution id	AO	variable-length required field
<b>2.00</b> renewed items	<b>BM</b>	<b>variable-length optional field (this field sent for each renewed item)</b>
<b>2.00</b> unrenewed items	<b>BN</b>	<b>variable-length optional field (this field sent for each unrenewed item)</b>
screen message	AF	variable-length optional field
print line	AG	variable-length optional field

## Standard Protocol Rules and Regulations

### Standalone Messages

Each message/response pair should stand on its own, irrespective of any previous or future message/response pair. For instance, it is not required for the SC to send a Patron Status Request Message and for the ACS to respond to it in order for the SC to send a Checkout Message; the Checkout Message contains everything that should be needed for the ACS to perform a Checkout operation and construct a Checkout Response Message. Similarly, although the SC might send an End Session Message to signal the end of a patron's activity of checking out books, there may be no End Session Message sent to signal the end of a patron's activity of checking in books until some time after the patron is actually done and a timer expires due to lack of patron activity, since the SC may not know when the patron is done. It is intended that each protocol message/response pair be independent of any other protocol message/response pair.

### Commands

Command identifiers that are unrecognized should be ignored. This allows new commands to be added to the protocol in the future, without adversely affecting software written for earlier versions of the protocol.

All recognized commands sent by the SC to the ACS require a response from the ACS.

The ACS Status Message Response will not be sent by the ACS unsolicited. When the ACS wishes a change of status, it will send an ACS Status message as the response to the next message sent to it by the SC. The SC will accept the new status and then send its command again (unless it happened to be an SC Status message).

### Fields

Fields with unrecognized field identifiers should be ignored. This allows new fields to be added to the protocol in the future, without adversely affecting software written for earlier versions of the protocol.

### Packet Format

Messages to and from the ACS have the same general format. The message packet begins with a command identifier. The command identifier is followed by fixed-length fields without field identifiers, and then by fixed- and variable-length fields with field identifiers. The message ends with a carriage return.

Fixed-length fields must appear in the order given in the specification for each message.

Fields with fields identifiers may be sent in any order following the fixed-length fields. For some fields in some messages, multiple fields of the same type may be included in a single message.

In general the packet contains only ASCII characters. The command identifier is two ASCII characters, the fixed and variable-length fields are composed of ASCII characters, field identifiers are ASCII characters, and the message terminator is an ASCII character.

The default character set will be English 850 (as defined in the Microsoft MS DOS manual). If another character set is required, the SC and the ACS must mutually define the character set.



## Message Terminator

All messages must end in a carriage return (hexadecimal 0d). This character is interpreted as the last character in a message and cannot be used elsewhere as a character in a message.

## Nulls

Null codes (hexadecimal code 00) cannot appear anywhere in a message.

## Fixed-length fields

Fixed-length required fields must contain specific information and cannot be left blank.

## Variable-length fields

Variable-length fields start with 2 field identifier characters, followed by 0 to 255 characters from a mutually agreed upon character set, and end with a | (code hexadecimal 7C). The | is a delimiter so it cannot appear anywhere except as the last character of the field. Some languages use code 7C as a printable character. In this case, another delimiter character must be defined. The field delimiter code should be configurable in the SC.

field = <field identifier characters><from 0 to 255 ASCII characters><delimiter>

When variable-length or optional fields from the ACS are not used, they should be left out entirely.

Beginning with Ver. 2.00 of the protocol, the following rules are followed in assigning field identifiers:

- all fields added to pre-existing messages are assigned field identifiers
- all variable-length fields are assigned field identifiers
- all optional fields are assigned field identifiers
- required fields in new messages that are fixed in length and are not perceived to be general-purpose fields (not useful in other messages) are not assigned field identifiers
- any field assigned a field identifier, whether fixed or variable in length, must end with a delimiter character.

This will hopefully make it easier to maintain backward compatibility.

Only displayable characters (no control characters) should be included in print or display messages from the ACS.

## Establishing a Connection

This protocol does not define how a communications session between the SC and ACS is established, only the format of the data transferred between the SC and the ACS once they have established a connection.

## Error Handling

### Checksums and Sequence Numbers

The protocol allows extra error detection to be enabled, over and above any error detection provided by the communications medium's protocol. When error detection is enabled, a sequence number field, followed by a checksum field, is appended to every message as defined in previous pages. When included in a message, the sequence number field should always be the second-to-last field, the checksum field should be the last field, and they should be followed by a carriage return (see above) as the last character in the message.

The checksum is four ASCII character digits representing the binary sum of the characters including the first character of the transmission and up to and including the checksum field identifier characters.

To calculate the checksum add each character as an unsigned binary number, take the lower 16 bits of the total and perform a 2's complement. The checksum field is the result represented by four hex digits.

To verify the correct checksum on received data, simply add all the hex values including the checksum. It should equal zero.

The sequence number is a single ASCII digit, '0' to '9'. When error detection is enabled, the SC will increment the sequence number field for each new message it transmits. The ACS should verify that the sequence numbers increment as new messages are received from the 3M SelfCheck system. When error detection is enabled, the ACS response to a message should include a sequence number field also, where the sequence number field's value matches the sequence number value from the message being responded to.

Note that, even though both the sequence number and checksum fields have field identifiers, neither field utilizes the field delimiter character. Both fields are fixed in length.

### **SC System Error Handling**

When a message is sent from the SC to the ACS, the SC waits for a response until a timer expires.

If the timer expires without a response, the message is re-transmitted, until the maximum number of retries is reached.

If a response message is received but is found to have a checksum error, the SC transmits a "Request ACS Resend" message. If further errors occur, the "Request ACS Resend" message is re-transmitted until the maximum number of retries is reached.

If the ACS returns a "Request SC Resend" message, the original message is re-transmitted, provided that the maximum number of retries is not exceeded, and the last message sent was not itself a "Request ACS Resend" message.

Should the maximum number of retries be reached without a valid response being received, or if the SC receives a "Request SC Resend" message in response to having sent a "Request ACS Resend" message, the SC should conclude that communications with the ACS have failed.

If the SC receives a response message with a valid checksum, but the sequence number does not match the sequence number of the message sent, the SC will discard the response and wait for another, valid response from the ACS (and probably timeout doing so).

### **ACS System Error Handling**

When a message is received from the SC that has a checksum error, the ACS should respond with a "Request SC Resend" message.

When the ACS responds to a valid message it may receive a "Request ACS Resend" message. In such a case the previous response should be retransmitted, even if it was itself a "Request SC Resend" message. If no response message had been transmitted, then a "Request SC Resend" message should be sent.

If the ACS receives a message in which the message checksum and sequence number match the previous message received from the SC, the ACS should re-send its last response.

## Protocol Version Compatibility

- a) If SC protocol version > ACS system protocol version  
SC will take responsibility for deciding if it can operate in a mode compatible with an older version ACS system.
- b) If SC protocol version < ACS system protocol version  
Each version of Standard Protocol will include in its specification the minimum version of the SC Protocol with which it is compatible. The ACS system should refuse to talk to a version of the protocol which is older than the specified minimum. The minimum compatible version of the Standard Protocol release 1.00 is 1.00.

For example, V3.00 of the standard protocol might have as its minimum compatible version V2.50. This version of ACS system would operate only with SC's running protocol version 2.50 or higher.

If the ACS system detects an incompatible version it should send an ACS system status message indicating that the ACS system is not on-line, with an appropriate error message for the SC screen.

### Protocol Extensions

If you extend the protocol for the purpose of communicating to a device other than a 3M SelfCheck system, you are requested to send documentation of your extensions to 3M. In an effort to make this protocol a general-purpose standard, 3M will try to incorporate into the 3M Standard Interchange Protocol those extensions that are deemed to be general-purpose, and will also try to avoid re-using Message IDs and Field IDs that are in use in your extensions.

<b>Field Definitions</b>																														
<u>Field Name</u>	<u>Field ID</u>	<u>Field Description</u>																												
ACS renewal policy		1-char, fixed-length field: Y or N. A Y indicates that the SC is allowed by the ACS to process patron renewal requests as a policy. This field was called "renewal ok" in Version 1.00 of the protocol.																												
alert		1-char, fixed-length field: Y or N. A Y in the alert field will generate an audible sound at the SC. The alert will indicate conditions like articles on hold, articles belonging to another library branch, or other alert conditions as determined by the ACS. The alert signal will alert the library staff to special article handling conditions during discharging operations.																												
available		1-char, fixed-length field: Y or N. A Y indicates that the item is available; it is not checked out or on hold.																												
blocked card msg	AL	variable-length field. This field indicates the reason the patron card was blocked.																												
cancel	BI	1-char field: Y or N. This field should be set to Y for a Checkout command being used to cancel a failed Checkin command, or for a Checkin command being used to cancel a failed Checkout command. It should be set to N for all other Checkout or Checkin commands.																												
card retained		1-char, fixed-length field: Y or N. This field notifies the ACS that the patron's library card has been retained by the SC. The ACS may ignore this field or notify the library staff that the patron's card has been retained by the SC.																												
charged items	AU	variable-length field. This field should be sent for each charged item.																												
charged items count		4-char, fixed-length field. This field should contain the number of charged items for this patron, from 0000 to 9999. If this information is not available or unsupported this field should contain four blanks (code \$20).																												
charged items limit	CB	4-char, fixed-length field. This field should contain the limit number of charged items for this patron from 0000 to 9999.																												
checkin ok		1-char, fixed-length field: Y or N. A Y indicates that the SC is allowed to check in items.																												
checkout ok		1-char, fixed-length field: Y or N. A Y indicates that the SC is allowed to check out items.																												
checksum	AZ	4-char, fixed-length message checksum, used for checksumming messages when error detection is enabled.																												
circulation status		2-char, fixed-length field (00 thru 99). The circulation status of an item. The following statuses are defined: <table border="1" style="margin-left: 20px;"> <thead> <tr> <th><u>Value</u></th> <th><u>Status</u></th> </tr> </thead> <tbody> <tr><td>1</td><td>other</td></tr> <tr><td>2</td><td>on order</td></tr> <tr><td>3</td><td>available</td></tr> <tr><td>4</td><td>charged</td></tr> <tr><td>5</td><td>charged; not to be recalled until earliest recall date</td></tr> <tr><td>6</td><td>in process</td></tr> <tr><td>7</td><td>recalled</td></tr> <tr><td>8</td><td>waiting on hold shelf</td></tr> <tr><td>9</td><td>waiting to be re-shelved</td></tr> <tr><td>10</td><td>in transit between library locations</td></tr> <tr><td>11</td><td>claimed returned</td></tr> <tr><td>12</td><td>lost</td></tr> <tr><td>13</td><td>missing</td></tr> </tbody> </table>	<u>Value</u>	<u>Status</u>	1	other	2	on order	3	available	4	charged	5	charged; not to be recalled until earliest recall date	6	in process	7	recalled	8	waiting on hold shelf	9	waiting to be re-shelved	10	in transit between library locations	11	claimed returned	12	lost	13	missing
<u>Value</u>	<u>Status</u>																													
1	other																													
2	on order																													
3	available																													
4	charged																													
5	charged; not to be recalled until earliest recall date																													
6	in process																													
7	recalled																													
8	waiting on hold shelf																													
9	waiting to be re-shelved																													
10	in transit between library locations																													
11	claimed returned																													
12	lost																													
13	missing																													

<b>Field Definitions</b>																				
<u>Field Name</u>	<u>Field ID</u>	<u>Field Description</u>																		
currency type	BH	<p>3-char, fixed-length field. The value for currency type follows ISO Standard 4217:1995, using the 3-character alphabetic code part of the standard. A portion of the standard is provided here as examples:</p> <table border="1"> <thead> <tr> <th><u>Value</u></th> <th><u>Definition</u></th> </tr> </thead> <tbody> <tr> <td>USD</td> <td>US Dollar</td> </tr> <tr> <td>CAD</td> <td>Canadian Dollar</td> </tr> <tr> <td>GBP</td> <td>Pound Sterling</td> </tr> <tr> <td>FRF</td> <td>French Franc</td> </tr> <tr> <td>DEM</td> <td>Deutsche Mark</td> </tr> <tr> <td>ITL</td> <td>Italian Lira</td> </tr> <tr> <td>ESP</td> <td>Spanish Peseta</td> </tr> <tr> <td>JPY</td> <td>Yen</td> </tr> </tbody> </table>	<u>Value</u>	<u>Definition</u>	USD	US Dollar	CAD	Canadian Dollar	GBP	Pound Sterling	FRF	French Franc	DEM	Deutsche Mark	ITL	Italian Lira	ESP	Spanish Peseta	JPY	Yen
<u>Value</u>	<u>Definition</u>																			
USD	US Dollar																			
CAD	Canadian Dollar																			
GBP	Pound Sterling																			
FRF	French Franc																			
DEM	Deutsche Mark																			
ITL	Italian Lira																			
ESP	Spanish Peseta																			
JPY	Yen																			
current location	AP	variable-length field; the current location of the item. 3M SelfCheck system software could set this field to the value of the 3M SelfCheck system terminal location on a Checkin message.																		
date / time sync		18-char, fixed-length field: YYYYMMDDZZZZHHMMSS. May be used to synchronize clocks. The date and time should be expressed according to the ANSI standard X3.30 for date and X3.43 for time. 000000000000000000 indicates a unsupported function. When possible local time is the preferred format.																		
desensitize		1-char, fixed-length field: Y or N or (obsolete)U. A Y in this field indicates that the SC unit should desensitize the article. An N in this field indicates that the article will not be desensitized, i.e. some non-circulation books are allowed to be checked out, but not removed from the library. A U indicates that the ACS does not know if the item should or should not be desensitized, and will be treated by the SC the same as an N.																		
due date	AH	variable-length field. This date field is not necessarily formatted with the ANSI standard X3.30 for date and X3.43 for time. Since it is a variable-length field the ACS can send this date field in any format it wishes.																		
e-mail address	BE	variable-length field. The patron's e-mail address.																		
end item	BQ	variable-length field. The number of the last item to be returned. The Patron Information message allows the SC to request the ACS to send a list of items that a patron has checked out, or that are overdue, etc. This field specifies the number in that list of the last item to be sent to the SC. For instance, if the SC had requested - via the summary, start item, and end item fields of the Patron Information message - to have the seventh through twelfth items in the list of the patron's overdue items sent in the Patron Information response, this field would have the value "12". A numbering system that starts with 1 is assumed. This allows the requester to have control over how much data is returned at a time, and also to get the whole list in sequential or some other order using successive messages/responses.																		
end session		1-char, fixed-length field: Y or N. Y indicates that the ACS has ended the patron's session in response to the End Patron Session message. N would be an error condition.																		
expiration date	BW	18-char, fixed-length field: YYYYMMDDZZZZHHMMSS; the date, if any, that the hold will expire.																		
fee acknowledged	BO	<p>1-char field: Y or N.</p> <p>If this field is N in a Checkout message and there is a fee associated with checking out the item, the ACS should tell the SC in the Checkout Response that there is a fee, and refuse to check out the item. If the SC and the patron then interact and the patron agrees to pay the fee, this field will be set to Y on a second Checkout message, indicating to the ACS that the patron has acknowledged the fee and checkout of the item should not be refused just because there is a fee associated with the item.</p>																		

<b>Field Definitions</b>																						
<u>Field Name</u>	<u>Field ID</u>	<u>Field Description</u>																				
		<p>One could say that use of the fee acknowledged field should not be necessary for renewals - the patron should already know that there is a fee associated with the item, having agreed to it when the item was initially checked out - but the field is provided as an optional field with the renewal messages for those systems that take the view that patrons should always acknowledge fees.</p> <p>Presumably, a Y value in the fee acknowledged field of a Renew All message would mean that the patron had agreed to all fees associated with all items being renewed.</p> <p>Fee acknowledged exists as an optional field on the Hold command to acknowledge a charge to put a hold on an item. Some libraries, under some conditions, levy a charge to put a hold on an item; fee acknowledged could be used in these situations to allow the hold charge to be agreed to before the hold was actually put on the item.</p>																				
fee amount	BV	variable-length field. This contains a money amount in whatever currency type is specified by the currency type field of the same message. For example, "115.57" could specify \$115.57 if the currency type was USD (US Dollars).																				
fee identifier	CG	variable-length field. Identifies a specific fee, possibly in combination with fee type. This identifier would have to be user-selected from a list of fees.																				
fee limit	CC	variable-length field. This field indicates that the limiting value for fines and fees that the patron is allowed to accumulate in their account. It is a money amount in whatever currency type is specified by the currency type field of the same message. For example, "50.00" could specify \$50.00 if the currency type was USD (US Dollars).																				
fee type	BT	<p>2-char, fixed-length field (01 thru 99). Enumerated type of fee, from the following table:</p> <table border="1"> <thead> <tr> <th><u>Value</u></th> <th><u>Fee Type</u></th> </tr> </thead> <tbody> <tr><td>01</td><td>other/unknown</td></tr> <tr><td>02</td><td>administrative</td></tr> <tr><td>03</td><td>damage</td></tr> <tr><td>04</td><td>overdue</td></tr> <tr><td>05</td><td>processing</td></tr> <tr><td>06</td><td>rental</td></tr> <tr><td>07</td><td>replacement</td></tr> <tr><td>08</td><td>computer access charge</td></tr> <tr><td>09</td><td>hold fee</td></tr> </tbody> </table>	<u>Value</u>	<u>Fee Type</u>	01	other/unknown	02	administrative	03	damage	04	overdue	05	processing	06	rental	07	replacement	08	computer access charge	09	hold fee
<u>Value</u>	<u>Fee Type</u>																					
01	other/unknown																					
02	administrative																					
03	damage																					
04	overdue																					
05	processing																					
06	rental																					
07	replacement																					
08	computer access charge																					
09	hold fee																					
fine items	AV	variable-length field. This field should be sent for each fine item.																				
fine items count		4-char, fixed length field. This field should contain the number of fine items for this patron, from 0000 to 9999. If this information is not available or unsupported this field should contain four blanks (code \$20).																				
hold items	AS	variable-length field. This field should be sent for each hold item.																				
hold items count		4-char, fixed length field. This field should contain the number of hold items for this patron, from 0000 to 9999. If this information is not available or unsupported this field should contain four blanks (code \$20).																				
hold items limit	BZ	4-char, fixed-length field. This field should contain the limit number of hold items for this patron, from 0000 to 9999.																				
hold mode		<p>1-char, fixed-length field. If mode is :</p> <ul style="list-style-type: none"> <li>+ add patron to the hold queue for the item</li> <li>- delete patron from the hold queue for the item</li> <li>* change the hold to match the message parameters</li> </ul>																				
hold pickup date	CM	18-char, fixed-length field: YYYYMMDDZZZZHHMMSS. The date that the hold expires.																				
hold queue lengthCF		variable-length field. Number of patrons requesting this item.																				
hold type	BY	<p>1-char, fixed-length field (1 thru 9). The type of hold:</p> <table border="1"> <thead> <tr> <th><u>Value</u></th> <th><u>Hold Type</u></th> </tr> </thead> <tbody> </tbody> </table>	<u>Value</u>	<u>Hold Type</u>																		
<u>Value</u>	<u>Hold Type</u>																					

<b>Field Definitions</b>																																																												
<u>Field Name</u>	<u>Field ID</u>	<u>Field Description</u>																																																										
		1 other																																																										
		2 any copy of a title																																																										
		3 a specific copy of a title																																																										
		4 any copy at a single branch or sublocation																																																										
home address	BD	variable-length field; the home address of the patron.																																																										
home phone number	BF	variable-length field; the patron's home phone number.																																																										
institution id	AO	variable-length field; the library's institution ID.																																																										
item identifier	AB	variable-length field; the article bar-code. This information is needed by the SC to verify that the article that was checked in matches the article bar-code at the SC.																																																										
item properties	CH	variable-length field. This field may contain specific item information that can be used for identifying a item, such as item weight, size, security marker, etc. It may possibly used for security reasons. ACSs are encouraged to store this information in their database.																																																										
item properties ok		1-char field. A 'I' in this field indicates that the item properties have been stored on the ACS database. Any other value indicates that item properties were not stored.																																																										
language		3-char, fixed-length field. The ACS may use this field's information to format screen and print messages in the language as requested by the Patron. Code 000 in this field means the language is not specified.																																																										
		<table border="1"> <thead> <tr> <th><u>Language</u></th> <th><u>Code</u></th> </tr> </thead> <tbody> <tr><td>Unknown (default)</td><td>000</td></tr> <tr><td>English</td><td>001</td></tr> <tr><td>French</td><td>002</td></tr> <tr><td>German</td><td>003</td></tr> <tr><td>Italian</td><td>004</td></tr> <tr><td>Dutch</td><td>005</td></tr> <tr><td>Swedish</td><td>006</td></tr> <tr><td>Finnish</td><td>007</td></tr> <tr><td>Spanish</td><td>008</td></tr> <tr><td>Danish</td><td>009</td></tr> <tr><td>Portuguese</td><td>010</td></tr> <tr><td>Canadian-French</td><td>011</td></tr> <tr><td>Norwegian</td><td>012</td></tr> <tr><td>Hebrew</td><td>013</td></tr> <tr><td>Japanese</td><td>014</td></tr> <tr><td>Russian</td><td>015</td></tr> <tr><td>Arabic</td><td>016</td></tr> <tr><td>Polish</td><td>017</td></tr> <tr><td>Greek</td><td>018</td></tr> <tr><td>Chinese</td><td>019</td></tr> <tr><td>Korean</td><td>020</td></tr> <tr><td>North American Spanish</td><td>021</td></tr> <tr><td>Tamil</td><td>022</td></tr> <tr><td>Malay</td><td>023</td></tr> <tr><td>United Kingdom</td><td>024</td></tr> <tr><td>Icelandic</td><td>025</td></tr> <tr><td>Belgian</td><td>026</td></tr> <tr><td>Taiwanese</td><td>027</td></tr> </tbody> </table>	<u>Language</u>	<u>Code</u>	Unknown (default)	000	English	001	French	002	German	003	Italian	004	Dutch	005	Swedish	006	Finnish	007	Spanish	008	Danish	009	Portuguese	010	Canadian-French	011	Norwegian	012	Hebrew	013	Japanese	014	Russian	015	Arabic	016	Polish	017	Greek	018	Chinese	019	Korean	020	North American Spanish	021	Tamil	022	Malay	023	United Kingdom	024	Icelandic	025	Belgian	026	Taiwanese	027
<u>Language</u>	<u>Code</u>																																																											
Unknown (default)	000																																																											
English	001																																																											
French	002																																																											
German	003																																																											
Italian	004																																																											
Dutch	005																																																											
Swedish	006																																																											
Finnish	007																																																											
Spanish	008																																																											
Danish	009																																																											
Portuguese	010																																																											
Canadian-French	011																																																											
Norwegian	012																																																											
Hebrew	013																																																											
Japanese	014																																																											
Russian	015																																																											
Arabic	016																																																											
Polish	017																																																											
Greek	018																																																											
Chinese	019																																																											
Korean	020																																																											
North American Spanish	021																																																											
Tamil	022																																																											
Malay	023																																																											
United Kingdom	024																																																											
Icelandic	025																																																											
Belgian	026																																																											
Taiwanese	027																																																											
library name	AM	variable-length field; the library's name.																																																										
location code	CP	variable-length field; the location code of the SC unit. This code will be configurable on the SC.																																																										
login password	CO	variable-length field; the password for the SC to use to login to the ACS. It is possible for this field to be encrypted; see the "PWD algorithm" field's definition.																																																										
login user id	CN	variable-length field; the user id for the SC to use to login to the ACS. It is possible for this field to be encrypted; see the "UID algorithm" field's definition.																																																										
magnetic media		1-char, fixed-length field: Y or N or U. A 'Y' in this field indicates that this article is magnetic media and the SC will then handle the security discharge accordingly. A 'N' in this field indicates that the article is not magnetic media. A 'U' indicates that the ACS does not identify																																																										

<b>Field Definitions</b>																										
<u>Field Name</u>	<u>Field ID</u>	<u>Field Description</u>																								
		magnetic media articles. ACS vendors are encouraged to store and provide article magnetic media identification.																								
max print width		3-char, fixed-length field. This is the maximum number of characters that the SC printer can print in one line. If the ACS wants to print longer messages it can send them in another print line field.																								
media type	CK	3-char, fixed-length field; enumerated media type, from the following table: <table border="1"> <thead> <tr> <th><u>Value</u></th> <th><u>Media Type</u></th> </tr> </thead> <tbody> <tr><td>000</td><td>other</td></tr> <tr><td>001</td><td>book</td></tr> <tr><td>002</td><td>magazine</td></tr> <tr><td>003</td><td>bound journal</td></tr> <tr><td>004</td><td>audio tape</td></tr> <tr><td>005</td><td>video tape</td></tr> <tr><td>006</td><td>CD/CDROM</td></tr> <tr><td>007</td><td>diskette</td></tr> <tr><td>008</td><td>book with diskette</td></tr> <tr><td>009</td><td>book with CD</td></tr> <tr><td>010</td><td>book with audio tape</td></tr> </tbody> </table>	<u>Value</u>	<u>Media Type</u>	000	other	001	book	002	magazine	003	bound journal	004	audio tape	005	video tape	006	CD/CDROM	007	diskette	008	book with diskette	009	book with CD	010	book with audio tape
<u>Value</u>	<u>Media Type</u>																									
000	other																									
001	book																									
002	magazine																									
003	bound journal																									
004	audio tape																									
005	video tape																									
006	CD/CDROM																									
007	diskette																									
008	book with diskette																									
009	book with CD																									
010	book with audio tape																									
nb due date		18-char, fixed-length field: YYYYMMDDZZZZHHMMSS. This is the no block due date that articles were given during off-line (store and forward) operation.																								
no block		1-char, fixed-length field: Y or N. This field notifies the ACS that the article was already checked in or out while the ACS was not on-line. When this field is Y, the ACS should not block this transaction because it has already been executed. The SC can perform transactions while the ACS is off-line. These transactions are stored and will be sent to the ACS when it comes back on-line.																								
off-line ok		1-char, fixed-length field: Y or N. This field should be Y if the ACS supports the off-line operation feature of the SC. The ACS must also support no block charge requests from the SC when it comes back on-line.																								
ok		1-char, fixed-length field: 0 or 1. A '1' in this field indicates that the requested action was allowable and completed successfully. A '0' indicates that the requested action was not allowable or did not complete successfully. This field is described in the preliminary NISO standard Z39.70-199x.																								
on-line status		1-char, fixed-length field: Y or N. This field is provided by the ACS to indicate whether the system is on or off-line. For example the ACS can use this field to notify the SC that it is going off-line for routine maintenance.																								
overdue items	AT	variable-length field. This field should be sent for each overdue item.																								
overdue items count		4-char, fixed-length field. This field should contain the number of overdue items for this patron, from 0000 to 9999. If this information is not available or unsupported this field should contain four blanks (code \$20).																								
overdue items limit	CA	4-char, fixed-length field. This field should contain the limit number of overdue items for this patron, from 0000 to 9999.																								
owner	BG	variable-length field. The field might contain the name of the institution or library that owns the item.																								
patron identifier	AA	variable-length field; an identifying value for the patron.																								
patron password	AD	variable-length field. If the ACS stores the patron password in its database then the SC will prompt the patron for their password (PIN) and it will be sent to the ACS in this field. If this feature is not used by the ACS in the library then the field should be zero length if it is required in the command, and can be omitted entirely if the field is optional in the command.																								
patron status		14-char, fixed-length field. This field is described in the preliminary NISO standard Z39.70-199x. A Y in any position indicates that the condition is true. A blank (code \$20) in this position																								



<b>Field Definitions</b>																																
<u>Field Name</u>	<u>Field ID</u>	<u>Field Description</u>																														
		means that this condition is not true. For example, the first position of this field corresponds to "charge privileges denied" and must therefore contain a code \$20 if this patron's privileges are authorized.																														
		<table border="1"> <thead> <tr> <th style="text-align: left;"><u>Position</u></th> <th style="text-align: left;"><u>Definition</u></th> </tr> </thead> <tbody> <tr><td>0</td><td>charge privileges denied</td></tr> <tr><td>1</td><td>renewal privileges denied</td></tr> <tr><td>2</td><td>recall privileges denied</td></tr> <tr><td>3</td><td>hold privileges denied</td></tr> <tr><td>4</td><td>card reported lost</td></tr> <tr><td>5</td><td>too many items charged</td></tr> <tr><td>6</td><td>too many items overdue</td></tr> <tr><td>7</td><td>too many renewals</td></tr> <tr><td>8</td><td>too many claims of items returned</td></tr> <tr><td>9</td><td>too many items lost</td></tr> <tr><td>10</td><td>excessive outstanding fines</td></tr> <tr><td>11</td><td>excessive outstanding fees</td></tr> <tr><td>12</td><td>recall overdue</td></tr> <tr><td>13</td><td>too many items billed</td></tr> </tbody> </table>	<u>Position</u>	<u>Definition</u>	0	charge privileges denied	1	renewal privileges denied	2	recall privileges denied	3	hold privileges denied	4	card reported lost	5	too many items charged	6	too many items overdue	7	too many renewals	8	too many claims of items returned	9	too many items lost	10	excessive outstanding fines	11	excessive outstanding fees	12	recall overdue	13	too many items billed
<u>Position</u>	<u>Definition</u>																															
0	charge privileges denied																															
1	renewal privileges denied																															
2	recall privileges denied																															
3	hold privileges denied																															
4	card reported lost																															
5	too many items charged																															
6	too many items overdue																															
7	too many renewals																															
8	too many claims of items returned																															
9	too many items lost																															
10	excessive outstanding fines																															
11	excessive outstanding fees																															
12	recall overdue																															
13	too many items billed																															
payment accepted		1-char, fixed-length field: Y or N. A Y indicates that the ACS has accepted the payment from the patron and the patron's account will be adjusted accordingly.																														
payment type		2-char, fixed-length field (00 thru 99). An enumerated value for the type of payment, from the following table:																														
		<table border="1"> <thead> <tr> <th style="text-align: left;"><u>Value</u></th> <th style="text-align: left;"><u>Payment Type</u></th> </tr> </thead> <tbody> <tr><td>00</td><td>cash</td></tr> <tr><td>01</td><td>VISA</td></tr> <tr><td>02</td><td>credit card</td></tr> </tbody> </table>	<u>Value</u>	<u>Payment Type</u>	00	cash	01	VISA	02	credit card																						
<u>Value</u>	<u>Payment Type</u>																															
00	cash																															
01	VISA																															
02	credit card																															
permanent location	AQ	variable-length field. The location where an item is normally stored after being checked in.																														
personal name	AE	variable-length field; the patron's name.																														
pickup location	BS	variable-length field; the location where an item will be picked up.																														
print line	AG	variable-length field. Print line fields provide a way for the ACS to print messages on the SC printer. They are never required. When used, there can be one or more of these fields, which are then printed on consecutive lines of the printer. If they are too long, then the trailing portion of the field will be left out.																														
protocol version		4-char, fixed-length field: x.xx. The protocol version field contains the version number of the protocol that the software is currently using. The format of the version number should be expressed as a single numeral followed by a period then followed by two more numerals.																														
PWD algorithm		1-char, fixed-length field. Specifies the algorithm, if any, used to encrypt the login password field of the Login Message. '0' means the login password is not encrypted. The SC and the ACS must agree on an algorithm to use and must agree on the value to be used in this field to represent that algorithm.																														
queue position	BR	variable-length field. This field contains a numeric value for the patron's position in the hold queue for an item.																														
recall date	CJ	18-char, fixed-length field: YYYYMMDDZZZZHHMMSS. The date that the recall was issued.																														
recall items	BU	variable-length field. This field should be sent for each recalled item.																														
recall items count		4-char fixed-length field. This field should contain a count of the items that the patron still has checked out that have been recalled, from 0000 to 9999. If this information is not available or unsupported this field should contain four blanks (code \$20).																														
renewal ok		1-char, fixed-length field: Y or N. This field is needed to inform the SC that the material is already checked out. A 'Y' value means that the item was checked out to the same patron, so it is actually being renewed. An 'N' value means that the patron did not already have the item checked out.																														

		Field Definitions										
<u>Field Name</u>	<u>Field ID</u>	<u>Field Description</u>										
renewed count		4-char fixed-length field. A count of the number of items that were renewed.										
renewed items	BM	variable-length field. This field should be sent for each renewed item.										
resensitize		1-char, fixed-length field: Y or N. If the ACS checked in the article and it is appropriate to resensitize it, then this field should contain a 'Y'. If the article should not be resensitized, then this field should contain a 'N'. In this case an appropriate message could be sent in the screen message field.										
retries allowed		3-char, fixed-length field. Indicates the number of retries that are allowed for a specific transaction. 999 indicates that the retry number is unknown.										
return date		18-char, fixed-length field: YYYYMMDDZZZZHHMMSS. The date that an item was returned to the library, which is not necessarily the same date that the item was checked back in.										
SC renewal policy		1-char, fixed-length field: Y or N. If this field contains a 'Y' then the SC has been configured by the library staff to do renewals. 'N' means the SC has been configured to not do renewals. This field was called "renewals allowed" in Version 1.00 of the protocol.										
screen message	AF	variable-length field. Screen message fields provide a way for the ACS to display messages on the SC screen. They are never required. When used, there can be one or more of these fields, which are then displayed on consecutive lines of the screen. If they are too long, then the trailing portion of the field will be left out. The message can contain holds, fines, disabled card, library branch, or other information as provided by the ACS.										
security inhibit	CI	1-char, fixed-length field: Y or N. A 'Y' in this field will notify the SC to ignore the security status of the item.										
security marker		2-char, fixed-length field (00 thru 99). Enumerated security marker type. <table border="1" style="margin-left: 20px;"> <thead> <tr> <th><u>Value</u></th> <th><u>Security Marker Type</u></th> </tr> </thead> <tbody> <tr> <td>00</td> <td>other</td> </tr> <tr> <td>01</td> <td>None</td> </tr> <tr> <td>02</td> <td>3M Tattle-Tape Security Strip</td> </tr> <tr> <td>03</td> <td>3M Whisper Tape</td> </tr> </tbody> </table>	<u>Value</u>	<u>Security Marker Type</u>	00	other	01	None	02	3M Tattle-Tape Security Strip	03	3M Whisper Tape
<u>Value</u>	<u>Security Marker Type</u>											
00	other											
01	None											
02	3M Tattle-Tape Security Strip											
03	3M Whisper Tape											
sequence number	AY	1-char, fixed-length field; sequence number for the message, used for error detection and synchronization when error detection is enabled.										
sort bin	CL	variable-length field. This field should contain a bin number that indicates how the items should be sorted. The maximum practical number of sort bins for a patron using 3M SelfCheck system is probably only 3 or 4, but many digits are allowed to accommodate some sort of fantastic sorting device using a hierarchical bin numbering scheme.										
start item	BP	variable-length field. The number of the first item to be returned. The Patron Information message allows the SC to request the ACS to send a list of items that a patron has checked out, or that are overdue, etc. This field specifies the number in that list of the first item to be sent to the SC. For instance, if the SC had requested - via the summary, start item, and end item fields of the Patron Information message - to have the fifth through tenth items in the list of the patron's overdue items sent in the Patron Information response, this field would have the value "5". A numbering system that starts with 1 is assumed. This allows the requester to have control over how much data is returned at a time, and also to get the whole list in sequential or some other order using successive messages/responses.										
status code		1-char, fixed-length field: 0 or 1 or 2; the status of the SC unit. <table border="1" style="margin-left: 20px;"> <thead> <tr> <th><u>Value</u></th> <th><u>Definition</u></th> </tr> </thead> <tbody> <tr> <td>0</td> <td>SC unit is OK</td> </tr> <tr> <td>1</td> <td>SC printer is out of paper</td> </tr> <tr> <td>2</td> <td>SC is about to shut down</td> </tr> </tbody> </table>	<u>Value</u>	<u>Definition</u>	0	SC unit is OK	1	SC printer is out of paper	2	SC is about to shut down		
<u>Value</u>	<u>Definition</u>											
0	SC unit is OK											
1	SC printer is out of paper											
2	SC is about to shut down											
status update ok		1-char, fixed-length field: Y or N. ACS policy for the SC. A Y indicates that patron status updating by the SC is allowed, e.g., a patron's card status can be changed to blocked.										

<b>Field Definitions</b>																																				
<u>Field Name</u>	<u>Field ID</u>	<u>Field Description</u>																																		
summary		<p>10-char, fixed-length field. This allows the SC to request partial information only. This field usage is similar to the NISO defined PATRON STATUS field. A Y in any position indicates that detailed as well as summary information about the corresponding category of items can be sent in the response. A blank (code \$20) in this position means that only summary information should be sent about the corresponding category of items. Only one category of items should be requested at a time, i.e. it would take 6 of these messages, each with a different position set to Y, to get all the detailed information about a patron's items. All of the 6 responses, however, would contain the summary information. See Patron Information Response.</p> <table border="1"> <thead> <tr> <th><u>Position</u></th> <th><u>Definition</u></th> </tr> </thead> <tbody> <tr><td>0</td><td>hold items</td></tr> <tr><td>1</td><td>overdue items</td></tr> <tr><td>2</td><td>charged items</td></tr> <tr><td>3</td><td>fine items</td></tr> <tr><td>4</td><td>recall items</td></tr> <tr><td>5</td><td>unavailable holds</td></tr> </tbody> </table>	<u>Position</u>	<u>Definition</u>	0	hold items	1	overdue items	2	charged items	3	fine items	4	recall items	5	unavailable holds																				
<u>Position</u>	<u>Definition</u>																																			
0	hold items																																			
1	overdue items																																			
2	charged items																																			
3	fine items																																			
4	recall items																																			
5	unavailable holds																																			
supported messages	BX	<p>variable-length field. This field is used to notify the SC about which messages the ACS supports. A Y in a position means that the associated message/response is supported. An N means the message/response pair is not supported.</p> <table border="1"> <thead> <tr> <th><u>Position</u></th> <th><u>Message Command/Response pair</u></th> </tr> </thead> <tbody> <tr><td>0</td><td>Patron Status Request</td></tr> <tr><td>1</td><td>Checkout</td></tr> <tr><td>2</td><td>Checkin</td></tr> <tr><td>3</td><td>Block Patron</td></tr> <tr><td>4</td><td>SC/ACS Status</td></tr> <tr><td>5</td><td>Request SC/ACS Resend</td></tr> <tr><td>6</td><td>Login</td></tr> <tr><td>7</td><td>Patron Information</td></tr> <tr><td>8</td><td>End Patron Session</td></tr> <tr><td>9</td><td>Fee Paid</td></tr> <tr><td>10</td><td>Item Information</td></tr> <tr><td>11</td><td>Item Status Update</td></tr> <tr><td>12</td><td>Patron Enable</td></tr> <tr><td>13</td><td>Hold</td></tr> <tr><td>14</td><td>Renew</td></tr> <tr><td>15</td><td>Renew All</td></tr> </tbody> </table>	<u>Position</u>	<u>Message Command/Response pair</u>	0	Patron Status Request	1	Checkout	2	Checkin	3	Block Patron	4	SC/ACS Status	5	Request SC/ACS Resend	6	Login	7	Patron Information	8	End Patron Session	9	Fee Paid	10	Item Information	11	Item Status Update	12	Patron Enable	13	Hold	14	Renew	15	Renew All
<u>Position</u>	<u>Message Command/Response pair</u>																																			
0	Patron Status Request																																			
1	Checkout																																			
2	Checkin																																			
3	Block Patron																																			
4	SC/ACS Status																																			
5	Request SC/ACS Resend																																			
6	Login																																			
7	Patron Information																																			
8	End Patron Session																																			
9	Fee Paid																																			
10	Item Information																																			
11	Item Status Update																																			
12	Patron Enable																																			
13	Hold																																			
14	Renew																																			
15	Renew All																																			
terminal location	AN	variable-length field. The ACS could put the SC's location in this field.																																		
terminal password	AC	variable-length field. This is the password for the SC unit. If this feature is not used by the ACS in the library then the field should be zero length if it is required in the command, and can be omitted entirely if the field is optional in the command.																																		
third party allowed		1-char, fixed-length field: Y or N. If this field contains an 'N' then the ACS should not allow third party renewals. This allows the library staff to prevent third party renewals from this terminal.																																		
timeout period		3-char, fixed-length field. This timeout period until a transaction is aborted should be a number expressed in tenths of a second. 000 indicates that the ACS is not on-line. 999 indicates that the time-out is unknown.																																		
title identifier	AJ	variable-length field. Identifies a title; could be a bibliographic number or a title string.																																		
transaction date		18-char, fixed-length field: YYYYMMDDZZZZHHMMSS. All dates and times are expressed according to the ANSI standard X3.30 for date and X3.43 for time. The ZZZZ field should contain blanks (code \$20) to represent local time. To represent universal time, a Z character (code \$5A) should be put in the last (right hand) position of the ZZZZ field. To represent other time zones the appropriate character should be used; a Q character (code \$51) should be put in the last (right hand) position of the ZZZZ field to represent Atlantic Standard Time. When possible local time is the preferred format.																																		
transaction id	BK	variable-length field. This field should contain a transaction id that is assigned by the ACS or by a payment device, for auditing purposes to track cash flow.																																		

<b>Field Definitions</b>		
<u>Field Name</u>	<u>Field ID</u>	<u>Field Description</u>
UID algorithm		1-char, fixed-length field. Specifies the algorithm, if any, used to encrypt the login user id field of the Login Message. '0' means the login user id is not encrypted. The SC and the ACS must agree on an algorithm to use and must agree on the value to be used in this field to represent that algorithm. Few, if any, systems will want to encrypt the user id.
unavailable holds count		4-char fixed-length field. This field should contain the number of unavailable holds for this patron, from 0000 to 9999. If this information is not available or unsupported this field should contain four blanks (code \$20).
unavailable hold items	CD	variable-length field. This field should be sent for each unavailable hold.
unrenewed count		4-char fixed-length field; a count of the number of items that were not renewed.
unrenewed items	BN	variable-length field. This field should be sent for each unrenewed item. It could include a reason that the item was not renewed.
valid patron	BL	1-char field: Y or N. A Y in this field is used to indicate that the patron bar-code is valid, is on the database. An N indicates that the patron is not a valid patron.
valid patron password	CQ	1-char field: Y or N. A Y in this field is used to indicate that the patron password is valid. An N indicates that the patron password is not valid.

**Field identifiers for variable-length or optional fields.**

These are each ASCII characters:

patron identifier	= AA	
item identifier	= AB	
terminal password	= AC	
patron password	= AD	
personal name	= AE	
screen message	= AF	
print line	= AG	
due date	= AH	
title identifier	= AJ	
blocked card msg	= AL	
library name	= AM	
terminal location	= AN	
institution id	= AO	
current location	= AP	
permanent location	= AQ	
<b>2.00</b> <i>hold items</i>	= AS	
<b>2.00</b> <i>overdue items</i>	= AT	
<b>2.00</b> <i>charged items</i>	= AU	
<b>2.00</b> <i>fine items</i>	= AV	
sequence number	= AY	(used only when error detection is enabled)
checksum	= AZ	(used only when error detection is enabled)
<b>2.00</b> <i>home address</i>	= BD	
<b>2.00</b> <i>e-mail address</i>	= BE	
<b>2.00</b> <i>home phone number</i>	= BF	
<b>2.00</b> <i>owner</i>	= BG	
<b>2.00</b> <i>currency type</i>	= BH	
<b>2.00</b> <i>cancel</i>	= BI	
<b>2.00</b> <i>transaction id</i>	= BK	
<b>2.00</b> <i>valid patron</i>	= BL	
<b>2.00</b> <i>renewed items</i>	= BM	
<b>2.00</b> <i>unrenewed items</i>	= BN	
<b>2.00</b> <i>fee acknowledged</i>	= BO	
<b>2.00</b> <i>start item</i>	= BP	
<b>2.00</b> <i>end item</i>	= BQ	
<b>2.00</b> <i>queue position</i>	= BR	
<b>2.00</b> <i>pickup location</i>	= BS	
<b>2.00</b> <i>fee type</i>	= BT	
<b>2.00</b> <i>recall items</i>	= BU	
<b>2.00</b> <i>fee amount</i>	= BV	
<b>2.00</b> <i>expiration date</i>	= BW	
<b>2.00</b> <i>supported messages</i>	= BX	
<b>2.00</b> <i>hold type</i>	= BY	
<b>2.00</b> <i>hold items limit</i>	= BZ	
<b>2.00</b> <i>overdue items limit</i>	= CA	
<b>2.00</b> <i>charged items limit</i>	= CB	
<b>2.00</b> <i>fee limit</i>	= CC	
<b>2.00</b> <i>unavailable hold items</i>	= CD	
<b>2.00</b> <i>hold queue length</i>	= CF	
<b>2.00</b> <i>fee identifier</i>	= CG	

<b>2.00</b>	<i>item properties</i>	=	<i>CH</i>
<b>2.00</b>	<i>security inhibit</i>	=	<i>CI</i>
<b>2.00</b>	<i>recall date</i>	=	<i>CJ</i>
<b>2.00</b>	<i>media type</i>	=	<i>CK</i>
<b>2.00</b>	<i>sort bin</i>	=	<i>CL</i>
<b>2.00</b>	<i>hold pickup date</i>	=	<i>CM</i>
<b>2.00</b>	<i>login user id</i>	=	<i>CN</i>
<b>2.00</b>	<i>login password</i>	=	<i>CO</i>
<b>2.00</b>	<i>location code</i>	=	<i>CP</i>
<b>2.00</b>	<i>valid patron password</i>	=	<i>CQ</i>

### Message identifiers

Command messages sent by the SC to the ACS:

Patron Status Request	=	23
Checkout	=	11
Checkin	=	09
Block Patron	=	01
SC Status	=	99
Request ACS Resend	=	97
<b>2.00</b>	<i>Login</i>	= 93
<b>2.00</b>	<i>Patron Information</i>	= 63
<b>2.00</b>	<i>End Patron Session</i>	= 35
<b>2.00</b>	<i>Fee Paid</i>	= 37
<b>2.00</b>	<i>Item Information</i>	= 17
<b>2.00</b>	<i>Item Status Update</i>	= 19
<b>2.00</b>	<i>Patron Enable</i>	= 25
<b>2.00</b>	<i>Hold</i>	= 15
<b>2.00</b>	<i>Renew</i>	= 29
<b>2.00</b>	<i>Renew All</i>	= 65

Response messages sent by the ACS to the SC:

Patron Status Response	=	24
Checkout Response	=	12
Checkin Response	=	10
ACS Status	=	98
Request SC Resend	=	96
<b>2.00</b>	<i>Login Response</i>	= 94
<b>2.00</b>	<i>Patron Information Response</i>	= 64
<b>2.00</b>	<i>End Session Response</i>	= 36
<b>2.00</b>	<i>Fee Paid Response</i>	= 38
<b>2.00</b>	<i>Item Information Response</i>	= 18
<b>2.00</b>	<i>Item Status Update Response</i>	= 20
<b>2.00</b>	<i>Patron Enable Response</i>	= 26
<b>2.00</b>	<i>Hold Response</i>	= 16
<b>2.00</b>	<i>Renew Response</i>	= 30
<b>2.00</b>	<i>Renew All Response</i>	= 66

## *Revision History*

<b>Version</b>	<b>Change(s)</b>
2.11	Removed unused field identifiers for variable-length or optional fields section. Updated Library Systems Software Support contact information.
2.12	Removed incorrect summary field value.